

COSY™

4 DIGIT LED ALARM CLOCK With 12 Daily Programmable Alarms



Model 4DF4AL12

Features :

- ★ Jumbo 4" High bright RED LED Characters
- ★ Clock displays time in 24 Hour Format.
- ★ 12 programmable daily alarms.
- ★ Internal Battery backup maintains time during a power failure ,
The clock will start to display accurate time as soon as the power is restored.
- ★ Sturdy black ABS cabinet .
- ★ Simple push buttons to set Alarm times .

Operating Instructions

DAILY TIME SETTING :

Simultaneously keep pressed TIME button with any button H+ , M+ to set daily clock time.

DAILY ALARM SETTING :

Simultaneously keep pressed ALARM 1 button with H+ , M+ to set daily alarm 1.

Similarly set other 11 alarms . If any of 12 alarm time is not required then set that alarm time as 00:00 .To reset any alarm time to 00:00 simultaneously keep pressed RESET button with required alarm button.

At set alarm times clock sounds a 5 second long continuous beep followed by a 15 second long PIP-PIP alarm sound.

It will also activate a dry relay contact output for 5 seconds which can be used to connect any external bell , hooter etc. with maximum rating of 5 Amp current .

If required , internal alarm of clock can be kept switched off while relay output is still available.

Power : 12V DC , 5 Watts appx. (SMPS power adapter included for use with 100V to 240V AC)
Internal battery installed for keeping time in RTC chip : CR2032 (expected battery life is 5 years)

Size & weight: 17 inches x 6 inches x 2 inches , 2 kg appx.

Clock Accuracy: appx 2 minutes per month or better at room temp 25 Deg. Cent.

Recommended for : Schools ,Factories, Offices, Shops, Hotels & Restaurants,
Sports and Fitness Centres , Labs , Automobiles, ships etc.

Manufactured by:

COSY COMMUNICATIONS , 1, Indraprastha Enclave , Sewla, Majra, Dehradun - 248 171 (INDIA)

Tele:91-135-2640816 E-Mail: cosycom@gmail.com , Web : www.cosyclocks.com